


ヘリカルバディボックス機種一覧

Helical Buddybox Available Combination



公称減速比 Ratio		11	18	21	28	39	46	53	60	74	88	102	123	151	179	207	249	305
出力回転数 Output speed r/min	50Hz	136	83	71	54	39	33	28	25	20	17	15	12	10	8.4	7.3	6.0	4.9
	60Hz	164	100	86	64	46	39	34	30	24	21	18	15	12	10	8.7	7.2	5.9
モータ容量 Motor (kW×P)	0.1×4														●	●	●	●
	0.2×4									●	●	●	●	●	●	●	●	●
	0.25×4									●	●	●	●	●	●	●	●	●
	0.4×4			●	●	●	●	●	●	●	●	●	●	●	●	●	●	●
	0.55×4			●	●	●	●	●	●	●	●	●	●	●	●	●	●	●
	0.75×4	●	●	●	●	●	●	●	●		●	●	●	●	●	●	●	●
	1.1×4	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●
	1.5×4	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●
	2.2×4	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●
	3.0×4	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●
	3.7×4	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●
	5.5×4	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●
	7.5×4	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●		
	11×4	●	●	●	●	●	●	●	●	●	●	●	●	●				
	15×4	●	●	●	●	●	●	●	●	●	●	●						
	18.5×4	●	●	●	●	●	●	●	●	●	●							
	22×4	●	●	●	●	●	●	●	●	●								
	30×4	●	●	●	●	●	●	●										

公称減速比 Ratio		364	417	424	501	578	683	809	956	1117	1320	1656	1957	2272	2559	2944	3511	4365
出力回転数 Output speed r/min	50Hz	3.98	3.48	3.42	2.90	2.51	2.12	1.79	1.52	1.30	1.10	0.876	0.741	0.638	0.567	0.493	0.413	0.332
	60Hz	4.81	4.20	4.13	3.50	3.03	2.56	2.16	1.83	1.57	1.33	1.06	0.894	0.770	0.684	0.595	0.499	0.401
モータ容量 Motor (kW×P)	0.1×4	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	
	0.2×4	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	
	0.25×4	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	●	
	0.4×4	●		●	●	●	●	●	●	●	●	●	●	●	●	●	●	●
	0.55×4	●		●	●	●	●	●	●	●	●	●	●	●	●	●	●	
	0.75×4	●		●	●	●	●	●	●	●	●	●	●					
	1.1×4	●		●	●	●	●	●	●	●	●	●						
	1.5×4	●		●	●	●	●	●	●	●								
	2.2×4	●		●	●	●	●	●										
	3.0×4	●		●	●	●												
	3.7×4	●		●	●													